

ELECTRIC OXYGEN IODINE LASER

5

CROSS-REFERENCE TO RELATED APPLICATIONS

This application is a continuation-in-part application of Patent Cooperation Treaty Application Serial No. PCT/US00/23642, entitled "Electric Oxygen Iodine Laser," with an international filing date of August 28, 2000, published in English under PCT Article 21(2) on March 22, 2001, and the specification thereof is incorporated herein by reference. That application claimed priority to U.S.

10 Provisional Patent Application Serial No. 60/151,260, entitled "Electric Oxygen Iodine Laser," filed on August 27, 1999, and the specification thereof is also incorporated herein by reference.

This application claims the benefit of the filing of U.S. Provisional Patent Application Serial No. 60/278,329, entitled "Electric Oxygen Iodine Laser," filed on March 22, 2001, and the specification
15 thereof is incorporated herein by reference.

BACKGROUND OF THE INVENTION

Field of the Invention (Technical Field):

The present invention relates to lasers and pulse circuits and excited atomic state and plasma
20 generators related thereto.

SUMMARY OF THE INVENTION (DISCLOSURE OF THE INVENTION)

The present invention comprises a pulse circuit for generating an output pulse, wherein the pulse circuit comprises a power supply; at least one Blumlein line wherein each line comprises a front
25 end and an output end; a switch for grounding each front end of the at least one Blumlein line simultaneously; and a snubber for truncating the output pulse from the at least one Blumlein line. As described herein, this pulser circuit is useful for a variety of applications. In an embodiment of this pulser circuit, the circuit further comprises at least two Blumlein lines comprising electrically connected and simultaneously groundable front ends and serially connected output ends. In another

embodiment of this pulser circuit, the circuit comprises discharge electrodes for discharging the output pulse to a gas wherein each of the discharge electrodes optionally bound a tube configuration comprising a surface for heat exchange.

5 The present invention also comprises an inventive generator for generating an excited atomic state of a molecule. According to one embodiment, this particular generator comprises a power supply; a pulse circuit; and an excited atomic state generating region wherein the pulse circuit discharges a pulse to a gas in the region and thereby generates an excited atomic state of at least one molecule in the gas and wherein the gas optionally comprises at least one inert gas. In a
10 particular embodiment, the excited atomic state generating region optionally comprises electrodes, a loop, or a cavity wherein the cavity optionally comprises a resonant cavity or a capacitively coupled cavity (particularly useful for RF and microwave energy deposition). In another embodiment, the excited atomic state generating region optionally comprises a loop and at least two electrodes. In yet another embodiment, the excited atomic state generator optionally comprises an excited atomic state
15 generating region comprising a loop and at least one transformer core comprising at least one winding wherein the excited atomic state generating region loop forms a second winding of the at least one transformer core. In many of the embodiments of the present invention, particularly the generator and laser embodiments, removal of heat from the system is useful. For example, one embodiment of the generator comprises an excited atomic state generating region that further comprises a component of
20 a heat exchanger.

 The present invention also comprises a laser. In one embodiment, the laser comprises a power supply; a pulse circuit; an excited atomic state generating region wherein the pulse circuit discharges a pulse to a gas in the region and thereby generates an excited atomic state of at least
25 one molecule in the gas and wherein the gas optionally comprises at least one inert gas; and a resonant cavity for generating a laser beam. In a particular embodiment, the laser optionally comprises a heat exchanger for controlling the temperature of said excited atomic state generating region; and optionally comprising supersonic expansion nozzles for introducing the gas into the excited atomic state generating region.

2020-02-28

The present invention also comprises several inventive methods. For example, the present invention comprises a method of generating a plasma. In one embodiment this method comprises the steps of: a) providing a gas; b) applying a pulse to the gas to over-volt the gas to an E/N value above ionization breakdown thereby forming a plasma; c) applying additional pulses, above ionization breakdown of the gas, to sustain quasi-continuous ionization of the plasma; and d) causing a current flow to the plasma by applying an electric field comprising an E/N value less than the glow potential of the plasma. In a particular embodiment of this method the gas comprises O₂ and the method generates an excited atomic state of O₂ and optionally wherein the excited atomic state comprises O₂¹Δ.

The present invention also comprises a method for producing a laser beam. In one embodiment, this laser method comprises the steps of: a) providing a gas; b) applying a pulse to the gas to over-volt the gas to an electric field normalized to plasma density value above ionization breakdown thereby forming a plasma; c) applying additional pulses, above ionization breakdown of the gas, to sustain quasi-continuous ionization of the plasma; d) causing a current flow to the plasma by applying an electric field comprising an electric field normalized to plasma density value less than the glow potential of the plasma; e) contacting the plasma with a molecule of the gas to generate an excited atomic state of that molecule; f) contacting the excited molecule with iodine to excite the iodine; and g) lasing the excited iodine.

The present invention also includes a laser comprising a gas, a beam produced by the gas and a throat wherein the gas and beam pass through the throat. In one embodiment, the throat comprises a converging region and a diverging region to achieve supersonic flow of gas passing therethrough. This particular embodiment is optionally useful when a lasing molecule is capable of repetitive cycling over the length of a cavity. While iodine is suitable as a lasing molecule, this embodiment is not limited specifically to iodine.

A primary object of the present invention is to enable an electric oxygen iodine laser.

A primary advantage of the present invention is an efficient laser.

Other objects, advantages and novel features, and further scope of applicability of the present invention will be set forth in part in the detailed description to follow, taken in conjunction with the accompanying drawings, and in part will become apparent to those skilled in the art upon examination of the following, or may be learned by practice of the invention. The objects and advantages of the invention may be realized and attained by means of the instrumentalities and combinations particularly pointed out in the appended claims.

BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are incorporated into and form a part of the specification, illustrate several embodiments of the present invention and, together with the description, serve to explain the principles of the invention. The drawings are only for the purpose of illustrating a preferred embodiment of the invention and are not to be construed as limiting the invention. In the drawings:

Fig. 1 is a graph of a variety of reactions versus E/N in Townsend;

Fig. 2 is a perspective view of a loop configuration of a generator embodiment of the present invention;

Fig. 3 is a perspective view of a loop and electrode configuration of a generator embodiment of the present invention;

Fig. 4 is a cross-sectional view of a loop and core configuration of a generator embodiment of the present invention;

Fig. 5 is a diagrammatic view of a generator embodiment of the present invention;

Fig. 6a is a diagrammatic view of tube bank of a generator embodiment of the present invention;

Fig. 6b is a diagrammatic view of a housing of an embodiment for housing a tube bank, such as that shown in Fig. 6a;

Fig. 7 is a graph of excited oxygen species shown as density versus distance for a particular embodiment of the present invention;

Fig. 8a is a diagrammatic side view of a laser of an embodiment of the present invention;

Fig. 8b is a diagrammatic view of an injector block of an embodiment of the present invention;

Fig. 8c is a diagrammatic top view of the laser shown in Fig. 8a;

Fig. 9 is a diagrammatic view of a close-cycle laser according to an embodiment of the present invention;

Fig. 10 is a diagrammatic view of a pulser circuit and generator according to an embodiment of the present invention;

Fig. 11 is a diagrammatic view of a controlled avalanche circuit mechanical assembly according to an embodiment of the present invention;

Fig. 12 is a diagrammatic view of a circuit for floating a DC potential on top of a DC jump potential and a pulsed high voltage avalanche ionization potential according to an embodiment of the present invention;

Fig. 13 is a diagrammatic view of an embodiment for producing a beam substantially parallel to the direction of gas flow; and

Fig. 14 is a diagrammatic view of a beam of the embodiment shown in Fig. 13.

5

DESCRIPTION OF THE PREFERRED EMBODIMENTS

(BEST MODES FOR CARRYING OUT THE INVENTION)

The present invention pertains to pulse circuits, generation apparatus and methods of generating plasma and/or excited atomic molecular species, and lasers. The pulse circuits of the present invention comprise means for generating ultra-short pulses suitable for use in lasers. The generation apparatus and methods of the present invention comprise means for generating plasma and/or excited atomic molecular species. For example, various embodiments of the generators of the present invention are useful for exciting molecules to excited atomic states, wherein such molecules include, but are not limited to, oxygen, water, carbon monoxide, carbon dioxide, nitrogen, NO, NO_x, chlorine, fluorine, bromine, etc. This list is not exhaustive nor exclusive but given to show that the present invention is not limited to excitation of oxygen molecules. While the embodiments that follow focus primarily on excitation of oxygen and/or generation of a plasma in the presence of oxygen, it would be understood by one of ordinary skill in the art of physical chemistry that the apparatus and methods of the present invention are useful for generating plasma and exciting chemicals other than oxygen. Likewise, the pulse circuit of the present invention has uses other than for generator apparatus and/or lasers.

Particular embodiments of the present invention pertain to oxygen-iodine laser systems for use in a variety of industrial applications including metal-working applications such as cutting, welding, drilling, and surface modification. Currently, CO₂ and NdYag type lasers are used for such metal-working applications. CO₂ lasers possess good beam quality, high efficiency, scalability to very high power levels (without loss of beam quality), and are an economical source of laser power on a per watt basis; however, they suffer from a long wavelength (10.6 microns) and, therefore, cannot be focused to a tight spot at high power levels without causing plasma formation. The long wavelength

also prevents transmission via fiber optic cable and limits the ability to cut thick steel precisely and efficiently. Ultimately, a CO₂ laser cannot cut or weld steel more than a few inches deep. NdYag lasers operate at a much shorter wavelength, 1.06 microns, which is transmittable via fiber optic cable. The 1.06 micron NdYag wavelength beam, in combination with a suitable lens, allows for beam focusing to a spot area 100 times smaller, at 100 times greater beam intensity, compared to a 10.6 micron CO₂ wavelength beam. In general, the smaller wavelength beam of the NdYag laser does not cause plasma formation until reaching an intensity level that is 100 fold that of the level which causes air breakdown for the CO₂ laser (i.e., 10⁹ watts/cm² for NdYag versus 10⁷ watts/cm² for CO₂); however, maintenance of beam quality is a major problem of NdYag lasers scaled to a high average power -- high power allows for an increase in work process rate. For example, a 2 KW to 3 KW multi-mode NdYag laser produces a focal spot that is blurred to a 1000 fold greater area than that produced by a 60 watt diffraction limited NdYag laser. Increased focal spot size also leads to heat loss to the sidewalls of the laser's "keyhole" cut -- such heat loss can be a limiting factor in many cutting applications.

The oxygen-iodine laser systems of the present invention combine advantages of CO₂ and NdYag lasers while eliminating many of their disadvantages. An oxygen iodine (O₂-I*) laser operates at 1.315 microns and is thereby transmittable by fiber optic cable. The 1.315 micron wavelength allows for beam focusing characteristic of NdYag lasers operated below 60 watts average power. Likewise, the O₂-I* laser achieves an intensity of nearly 10⁹ watts/cm² without causing plasma formation or losing beam quality. Essentially, the O₂-I* laser is scalable to tens or hundreds of kilowatts -- megawatts for that matter -- without losing beam quality. This allows for a sharp focus at high power. For example, O₂-I* laser systems of the present invention can cut easily through 12 inch-thick steel because such systems deliver a power density that is orders of magnitude higher than the rate at which the steel absorbs energy through the keyhole walls. A more detailed description of O₂-I* laser systems of the present invention follows.

O₂-I* laser systems of the present invention deviate from traditional chemical O₂-I* laser systems (COIL systems). Traditional COIL systems require liquid chlorine, concentrated hydrogen

peroxide, and potassium hydroxide. During operation, these chemicals are provided at a substantial rate and mixed to form a chemical reaction that produces oxygen in a particular excited state called $O_2^1\Delta$ (O-2 singlet delta). In COIL systems, a flowstream of $O_2^1\Delta$ passes through a chilled heat exchanger to remove water vapor — an unwanted by-product of the chemical reaction. Next, the $O_2^1\Delta$ flowstream passes through a block of helium and iodine injection nozzles, then supersonic expansion nozzles that accelerate and cool the oxygen/helium/iodine stream to about Mach 2.8 and about 100 K. The I_2 , which may be carried in buffer gas (e.g., helium), is generally mixed into the O_2 and $O_2^1\Delta$ flowstream just upstream of the supersonic expansion nozzles.

During this process, I_2 molecules collide with $O_2^1\Delta$ and disassociate into two iodine atoms. The individual iodine atoms, in turn, collide with additional $O_2^1\Delta$ molecules whereby energy stored in $O_2^1\Delta$ molecules is then transferred to iodine atoms. The transfer of energy causes a "populating" of the iodine's upper laser level. The change in energy level process is positioned to occur either just upstream of, or within, an optical resonator which is transverse to the supersonic flowstream. The O_2 - I^* laser beam is produced and directed transverse to the supersonic flowstream by the optical resonator. The chemical flowstream, post-resonator, passes through a supersonic/subsonic diffuser that causes a "shock down" to subsonic flow. The subsonic chemical stream is simply discharged from the system, for example, to the atmosphere, usually with the aid of an ejector pump. The aforementioned COIL system operates in an open-cycle configuration because the chemicals pass through the system only once.

The present invention encompasses both open-cycle and closed-cycle configurations; however, as shown below, closed-cycle configurations impart substantial benefits to some industrial applications, as do semi-closed cycle configurations. The present invention allows for a semi closed-cycle operation by virtue of electrical excitation of oxygen. For purposes of this invention, semi closed-cycle operation means that less than approximately 10% of system gas is lost as percentage of gas flow rate and preferably, this percentage is less than approximately 5% while most preferably, this percentage is less than approximately 1%. Electrical excitation eliminates the need for liquid chlorine, concentrated hydrogen peroxide, and potassium hydroxide. In the preferred embodiments of

the present invention, electricity alone energizes the laser, transforming pure oxygen into $O_2^1\Delta$. Semi closed-cycle operation of a preferred embodiment of the present invention's O_2-I^* laser system is illustrated in Figure 9.

5 Unlike the COIL system, the closed-cycle operable, electrically driven system of the present invention allows for design of practical systems for industrial applications. For example, electrically driven O_2-I^* systems of the present invention comprise a laser that operates at 1.315 microns having the physical size, cost per watt, power scalability, and beam quality advantages of a closed-cycle, fast-flow CO_2 laser system.

10

 A preferred embodiment of a particular laser system of the present invention shares some operational similarities with a United States Air Force COIL system. The Air Force COIL system first provides for I_2 collisions with $O_2^1\Delta$ that disassociate I_2 into 2I and second, provides for additional iodine collisions with metastable oxygen whereby energy is resonantly transferred to iodine thereby exciting
15 the iodine to the upper laser level. The most significant difference between the aforementioned preferred embodiment and the Air Force COIL system is that instead of producing the oxygen singlet delta from a chemical reaction of basic hydrogen peroxide and chlorine, the oxygen singlet delta is produced directly from ground-state oxygen by means of cold plasma electrical excitation.

20 Normally, the required fractional conversion of oxygen into $O_2^1\Delta$ cannot be accomplished by using either conventional (self-sustained) discharges or microwave discharges, because in both instances heat production is excessive and limiting, and also the electric field ("E-field") normalized to plasma density ("E/N") values encountered are much too high. More specifically, E/N is a measure of the E-field normalized to the plasma density, which plays a controlling role in nearly all plasma
25 processes. E/N is typically measured in Townsends 1Td (1Townsend) = 10^{-17} volt-cm², a value equivalent to 263.9 volts/cm-Amagat. Therefore, an insufficient fraction of the input energy gets partitioned into the single reaction product of importance: $O_2^1\Delta$. Chemical kinetics/Boltzman electron energy distribution calculations reveal that the necessary concentrations of $O_2^1\Delta$ are generated only if the following (normally mutually exclusive) conditions are simultaneously met:

10086030-022702
2024-09-20 10:08:30

(1) A high specific energy deposition (approximately 100 KJ/mole O_2) must be applied to a large volume, low pressure (approximately 5 to 50 Torr) flowstream of oxygen. For instance, the system requires a volume that is scalable to produce whatever $O_2^1\Delta$ flowrate is required for a laser of specific power (e.g., a 100 KW laser might require on the order of 43 liters of total plasma volume, if operated at 15 Torr total stagnation pressure);

(2) The energy deposition must occur within approximately 10 milliseconds or less (generally due to kinetic losses);

10

(3) The electric field must be maintained well below the glow potential so that E/N values lie between approximately 7 and approximately 10 Townsends during the entire energy deposition period;

15

(4) The energy deposition process must be essentially isothermal; i.e., waste heat must be removed at a rate such that the maximum gas temperature does not build up beyond approximately 200°C; and

(5) Since self-sustained discharges cannot provide the aforementioned conditions, an external means of ionization must be used. The chosen method must not contribute substantially to the net thermal energy input, nor modify the electron energy distribution substantially over the drift condition calculated for $E/N \cong 10Td$. Condition (5), as well as the occurrence attachment instabilities, rule out the use of electron beam ionization, which otherwise would seem to pose a self-evident solution.

25

The theoretical $O_2^1\Delta$ yield verses the applied electric field/density, E/N in Townsends (Td), is shown in Figure 1. Here, the chemical branching efficiency ratios for all relevant reactions have been calculated for the electron energy distribution function corresponding to each E/N value. The graph presented in Figure 1 illustrates that, for E/N falling between 7 and 10 Td, 50% of the applied electrical pump energy is directly stored in the $O_2^1\Delta$ it produces. The graph also shows that at the electric field

necessary to sustain a normal glow discharge (i.e., $E/N = 40 \text{ Td}$), the amount of $O_2^1\Delta$ created is insufficient to sustain laser action.

In a preferred embodiment, the present invention's method of meeting the aforementioned
5 criteria uses: ultrahigh E/N (initially greater than approximately 180 Townsends); and ultrashort (τ is approximately 5-15 nanoseconds) pulses at a rep rate sufficient to maintain an average electron number density of approximately 10^{13} to approximately 10^{14} electrons/cm³ during pump period (typically approximately 20 KHz to approximately 40 KHz), while maintaining a constant DC pump field (or magnetically induced square wave potential) at the required pump value of E/N is approximately
10 10 Td. In most systems of the present invention, ultrashort pulses of less than approximately 75 nanoseconds are desired while preferably pulses are less than approximately 25 nanoseconds and most preferably, pulses are less than approximately 15 nanoseconds. Through experimentation and investigation of a large number of generator configurations, preferred configurations comprise an integral electrical excitation generator and a heat exchanger. These configurations allow isothermal
15 heat addition; i.e., rapid removal of waste heat is in equilibrium with internal rate of heat production. It is noted that the applied pump potential (E/N is approximately 10 Td) falls far below the electric field required to maintain ionization, therefore, a continuous sequence of ultra high voltage (E/N initially greater than or equal to approximately 180 Td) pulses are applied to renew the ionization lost while the field is being sustained at only 10 Td (under fully developed equilibrium conditions, for example, and at high repetition rates e.g., 20,000 to 40,000 pps or more), for example, the residual ionization
20 can reduce the E/N level needed to renew ionization from levels of approximately 180 Td to levels less than approximately 180 Td, in some instances, for example, down to levels of approximately 100 Td or less). These ionization pulses must be arrested limit each pulse to less than a few tens of nanoseconds duration. Any ionization pulses of order E/N greater than or equal to approximately 100
25 Td to approximately 180 Td (depending on the initial ionization number density) lasting longer than approximately 75 nanoseconds would lead to arc breakdown. Furthermore, ionization pulses lasting longer than a few tens of nanoseconds generates O^1D at a concentration which tends toward becoming deleterious. Of course the invention is not limited to the parameters set forth in this particular embodiment, for example, but not limited to, E/N is not limited to values given, the pulse

length is not limited to the values given, and the electron number density is not limited to the values given. Furthermore, the invention is not limited to oxygen iodine lasers, because the pulse circuits and generators of the present invention have other uses as well. Depending on the particular use and configuration of any particular embodiment, E/N values of 150 Td are within the scope of the present invention for over-volting, as well as, for example, but not limited to, electron number density values from 10^{12} to 10^{15} .

An example of a magnetic induction loop generator is illustrated in Figure 2. As shown in Figure 2, the generator **100** comprises a loop portion **102** and a measurement/gas exit portion **104**.

The loop portion **102** comprises a core for providing a polar pulse **108**, a current probe **110**, a core for main power pulses **112**, a gas loop **106** surrounded by a coolant shell **120**. As depicted, the cores **108**, **112** and the current probe surround the gas loop **106**. The gas loop **106** further comprises surface indicia, fins, ribs, etc. **122**, for increasing heat transfer to the coolant. The coolant shell comprises a coolant inlet **116** and a coolant outlet **118**.

While not an essential part of the apparatus, the measurement/gas exit portion **104** comprises a connection **140** to the gas loop **106**. The measurement/gas exit portion **104** also comprises a block for sensors and measurements **142**, a gas exit **144**, a fiber optic observation and/or communication connection **146**, electrical leads for a thermocouple or other suitable temperature measurement device **148**, and a pressure sensor device and/or port for measurement of pressure **150**. The block **142** optionally comprises windows and a sensor volume, such a block is known to one of ordinary skill in the art. The gas exit **144** optionally comprises a throttling valve or similar device for controlling gas flow.

In an embodiment of this inventive generator system, a sequence of ionization pulses are magnetically induced into the loop **106** by means of a METGLAS® (Allied Signal Inc., Morristown, New Jersey) (or ferrite core) transformer **112** or transformers. Another METGLAS® transformer **108** is used to induce a sub-breakdown potential, square wave into the loop **106**. Of course, a "perfect" square wave having instantaneous rise and fall is not achievable in practice; therefore, it is understood

that square waves referred to herein have a rise time and a fall time. In this particular embodiment of the present invention, each half cycle of the square wave is of sufficient duration as to drive a transformer's magnetic core to near saturation or to saturation. Likewise, the second half-cycle, which is, for example, of equal magnitude and opposite polarity to the prior half cycle, drives the core to near saturation or to saturation in an opposite manner. The cycling square wave acts to induce a substantially constant electric pump field (e.g., but not limited to, approximately 10 Td) for application to the loop to maintain electrons at their optimal temperature distribution for exciting O₂ into the desired O₂¹Δ state. The fact that the field reverses periodically whenever the core **112** reaches near saturation or saturation does not affect the process because of the relatively short cycling time as evidenced by the duration of the aforementioned ultrashort pulses.

In an embodiment of this particular example of a magnetic induction loop generator, as illustrated in Figure 2, the plasma path length through loop **106** comprises a length of approximately 60 cm, a cross-sectional area of approximately 0.7 cm² and a volume of approximately 40 cm³. In this embodiment, the gas flow path through the loop **106** comprises a length of approximately 30 cm and a cross-section of approximately 1.4 cm². In this embodiment, the exit volume (loop **106** to sensor/measurement block **142**) comprises a length of approximately 14 cm, a cross-sectional area of approximately 0.7 cm² and a volume of approximately 23.1 cm³.

Another embodiment of the present invention, more specifically of a magnetic induction loop generator **200**, is shown in Figure 3. This example comprises a loop portion **202** and a measurement/gas exit portion **204** (used to verify the proof of principle but not essential to this embodiment of the invention). The measurement/gas exit portion **204** comprises the same features as the measurement/gas exit portion **104** of generator **100**. Thus, reference to Figure 2 and its description is suggested for a description of measurement/gas exit portion **204**. The loop portion **202** of the embodiment shown in Figure 3 differs from the loop portion **102**, as shown in Figure 2, in several ways. Loop portion **202** comprises at least one pot core **212** and preferably four pot cores **212**, **212'**, **212''**, **212'''**. The loop portion **204** also comprises a current probe **210** and a core for providing a poker (avalanche) pulse **208**. A loop **206** passes through the at least one pot core **212**

wherein the loop **206** makes at least one turn or winding and preferably approximately three windings. Gas enters the loop **206** through at least one inlet **214**, which connects to and/or forms an anode **220**. Gas exits the loop through at least one gas exit **215**, which connects to and/or forms a cathode **222**. As shown in Figure 3, the gas exit **215** comprises a "T" wherein one path connects to the measurement/gas exit portion **204** and the other path exits through a dump valve and/or to a reservoir.

As shown in Figure 3, this generator system **200** comprises multi-turn transformer windings comprising segments of the loop **206** in series. "Controlled avalanche" pulses are induced in the loop **206** by means of at least one ferrite pot core transformer segment **212**. Again, the system is characterized by extremely short ionizing pulses (e.g., approximately tens of nanoseconds), ultrahigh E-field (e.g., approximately greater than or equal to 180 Td), and a delivered repetition rate of approximately tens of kilohertz. A sub-breakdown (10 Td) field (a continuous direct current) is delivered from a cathode **222** on one end of the loop to an anode **220** at the other end. In this embodiment, the direct current (DC) flows in parallel and in the same direction through two current paths (as shown in Figure 3) of the loop **206** while the ionization pulse current flows continuously around the entire loop **206**. Again, the DC's E-field is tuned to the resonant-like magnitude (E/N equals approximately 10 Td) which drives electron excitation of O_2 to form $O_2^1\Delta$.

Figure 4 illustrates an embodiment of the present invention comprising a cross-sectional view through a cylindrically configured transformer-coupled $O_2^1\Delta$ generator **300**. This embodiment comprises a single ferrite core **302** to transform both a sequence of approximately greater than or equal to approximately 150 Td ionization pulses, and a sub-breakdown potential, square-wave pump field as described in the embodiment shown in Figure 3. The ferrite core **302** comprises a coupled loop **304** lined with at least one heat exchanger **306**, preferably electrically isolated, to efficiently remove the thermal energy created by the discharge. The generator further comprises a gas inlet **308** and an exit **310** which connects to, for example, a laser channel **312**, for production of a laser beam **314**. This particular embodiment, while shown with a single core, optionally comprises multiple cores.

A preferred embodiment of the present invention is shown in Figure 5. Figure 5 shows a schematic of a two-tube version of a linear-type, DC-pumped $O_2^1\Delta$ generator. Actual operation of this preferred embodiment resulted in $O_2^1\Delta$ yields that were more than sufficient for use in an O_2 -I* laser system. Of course, the number of tubes used in this embodiment is adjustable to generate flow rates needed for a particular laser system. By way of illustration, Figure 6a shows a "strawman" apparatus for a $O_2^1\Delta$ generator configured to power, for example, but not limited to, a 5 MW continuous laser. Further description of the apparatus Figure 6a is given below. Figure 6b shows particular dimensions of an embodiment comprising the configuration shown in Figure 6a.

In reference to Figure 5, this particular generator embodiment **500** of the present invention comprises a generator with an integral heat exchanger **502**. The generator/heat exchanger **502** further comprises, for example, but not limited to, two tubes **506**, **506'** housed within a shell **504**. While two tubes are shown this embodiment is not limited to two tubes and, in general, the embodiment comprises at least one tube. In this particular example, tubes **506**, **506'** optionally comprise a length of approximately 1 meter, an inner diameter of approximately 1 cm, a material of construction of Be, or other suitable material, and fluting (or other surface indicia, etc.) on the inside to improve heat transfer.

Referring again to Figure 5, this embodiment further comprises an O_2 inlet **520**, optionally comprising a flow rate control mechanism, a He inlet **530**, optionally comprising a flow rate control mechanism, a gas cooling bath **540**, optionally comprising dry ice and/or alcohol(s), and a vacuum pump **550**. Of course use of more than one vacuum pump is possible and, for example, but not limited to, such pump(s) is(are) rated individually and/or collectively at a flow rate of approximately 150 CFM. The generator **500** further comprises a variety of measurement/sensor ports and/or devices, known to one of ordinary skill in the art. Such ports and/or devices are shown generally in Figure 5 (**510**, **510'**, **510''**, **510'''**) and comprise, for example, but not limited to, ports and/or devices for measurement and/or sensing of temperature, pressure, optical properties, and the like.

Figure 5 also depicts electronic circuitry **560** for providing pulses. One type of pulse is provided through circuitry **564**. In general, circuitry **564** provides a "jump start" pulse. For example, but not limited to, a 50 KV pulse from a circuit comprising at least one vacuum tube. Circuit **564** further comprises a power supply **565**, for example, but not limited to, a 50 KV power supply. Circuit **564** optionally comprises a connection **566**, for example, but not limited to, a fiber optic connection, to timing electronics **568**. Of course, "wireless" modes of connection, relying on electromagnetic transmission are also within the scope of the present invention. In turn, the timing electronics **568** optionally comprises a connection to a velonix driver **570**. The velonix driver optionally comprises a connection to another pulse circuit **562**. Pulse circuit **562** provides, for example, but not limited to, an approximately -180 KV pulse with a frequency of approximately 10 to approximately 25 KHz that floats approximately 25 KV above ground. Pulse circuit **562** optionally comprises a thyatron-based circuit. Power is provided to pulse circuit **562** through a power supply **572**, for example, but not limited to, a -45 KV power supply. Power from the power supply **572** passes through a command charger **574**. The pulse circuit **562** further optionally comprises a DC power supply **576**, for example, but not limited to, an approximately 12 KV to approximately 18 KV DC power supply. According to electronic circuitry **560**, the pulsers **562**, **564** further optionally comprise isolation transformers **582**, **584**. Such transformers **582**, **584** optionally comprise, for example, but not limited to, 50 KV low capacitance isolation transformers. As shown in Figure 5, the power supply **565** is connected to pulser **564** and further connected to ground, through the power supply and/or through additional circuitry **586**, such as, but not limited to, capacitive and/or resistive circuitry. The power supply **576** is connected to pulser **562** and further connected to ground, through the power supply and/or through additional circuitry **578**, **580**, such as, but not limited to, capacitive and/or resistive circuitry.

The embodiment shown in Figure 5 further optionally comprises plasma diagnostics, such as, but not limited to, avalanche current, avalanche voltage, pump current and/or pump voltage. The embodiment shown in Figure 5 further optionally comprises gas diagnostics, such as, but not limited to, pressure, mixture/composition, flowrates, and/or temperatures. The embodiment shown in Figure 5 further optionally comprises optical diagnostics and/or recorders. An optical diagnostics port **512** is shown in Figure 5.

10066030-022702
2027220-022702

In an experimental apparatus according to this embodiment, a two tube generator was used wherein the tubes were submerged in a flouorinert dielectric liquid bath which was, in turn, maintained at dry ice temperatures, approximately -78.5°C , by means of circulating pumps. Each tube was
5 injected with metastable helium to pre-ionize the gas volume while a predominantly O_2 flowstream (with some helium) flowed through the tubes at approximately Mach 0.3 to approximately Mach 0.5.

Operation of this aforementioned system comprises, for example, but not limited to, application of up to approximately 180,000 volt pulses of approximately 30 nanosecond duration that
10 are generated at the rate of approximately 25,000 pulses per second. Application of these pulses created ionization of the gas contained in the tubes. Between pulses, the ionization number density fell by about 15% (the percentage fall is dependent on pressure); however, each succeeding pulse compensated for this loss in number density. The emergent gas flowed through an optical diagnostic cell and into a 150 CFM vacuum pump. The ionizing pulse train floated on top of a pure DC electric
15 field provided by an approximately 3 KV to approximately 5 KV power supply, which produced about 250 mA of current (average) in each tube. The $\text{O}_2^1\Delta$ yield was spectroscopically determined and exceeded 16% in pressures of several Torr of pure O_2 . This particular preferred embodiment is a configuration that provides a basis for additional preferred embodiments of laser systems to be discussed.

20

The generation of $\text{O}_2^1\Delta$, along with other competing processes, has been theoretically calculated along the length of the tubes subject to excitation as described above. The graph of the calculation, Figure 7, shows that under these conditions the tube will generate its maximum yield of $\text{O}_2^1\Delta$ if its length is approximately 42 cm. Beyond approximately 42 cm, the "pooling" process causes
25 the creation of $\text{O}_2^1\Sigma$ to dominate. At 42 cm, the theoretical yield Y (fraction $\text{O}_2^1\Delta/\text{O}_2^3\Sigma$) is approximately 29% — a value sufficient to produce superb laser performance. Under differing conditions the optimal length optionally differs, for example, but not limited to, lengths upto and beyond approximately one meter in length are within the scope of the present invention.

Referring to Figure 6a, a "strawman" apparatus 600 for a $O_2^1\Delta$ generator configured to power, for example, but not limited to, a 5 MW continuous laser. As shown, the strawman apparatus 600 further comprises at least one individual bank of plasma tubes 602, 602'. The banks further comprise plasma tubes 604, 604' and current returns 606, 606', 606'', 606'''. Surrounding, or spaced between, each bank 602, 602' is a heat exchange fluid supply 608, 608', 608''.

In summary, preferred embodiments of the present invention comprises an electric oxygen iodine laser that comprises a generator for generating $O_2^1\Delta$ wherein the $O_2^1\Delta$ generator comprises:

(1) A means for generating low-level, pre-ionization of at least one chemical species -- "pre-ionization means." In an aforementioned example, metastable helium was generated using an electric discharge pre-ionization generator, thereafter, the metastable helium was injected into a flowstream. Other means of achieving pre-ionization include: (a) dielectric barrier discharges; (b) photo-ionization; (c) X-ray ionization; (d) electron beam injection; (e) brush-cathode induced "runaway" electrons; (f) microwave; (g) RF induction (capacitively or magnetically induced); and/ or (H) a nuclear radiation source;

(2) A means for sustaining a significant level of quasi-continuous ionization, for example, wherein such means comprises generation and application of a rapid sequence of ultrashort, ultrahigh voltage pulses to at least one pre-ionized chemical species -- herein referred to as a "pulsing means." Where means for sustaining comprises ultrashort, ultrahigh voltage pulses, pulse magnitude significantly exceeds the arc potential required for creation of an avalanche of ionization to a degree (on the order, for example, but not limited to, of approximately 10^{12} to approximately 10^{15} electrons/cm³) while pulse duration is sufficiently short as to prevent arc formation and to minimize formation of undesirable excited state oxygen, e.g., the O^1D state. Pulse duration, or pulse length, is preferably less than a few tens of nanoseconds, and in all instances, less than approximately 75 nanoseconds, and most preferably less than approximately 15 nanoseconds. In addition the pulse energy is capable of "over-volting" the plasma in its original pre-ionized state to typically an initial E/N of, for example, but not limited to, approximately 150 Td to approximately 180 Td. Following the initial

ionization pulse of E/N equal to, for example, but not limited to, approximately 150 Td to approximately 180 Td, subsequent ionization pulses taper off to a lower E/N value of E/N equal to approximately 100 Td to approximately 120 Td in response to an increasing value of electron number density. As a result, the intended average quasi-continuous number density (approximately 10^{12} to 10^{15} electrons/cm³) is controlled and maintained. The pulser circuit is especially designed to provide the initial 180 Td "jump starter" pulse, then fall off to a suitable, maintained E/N value by means of an interaction between the circuit and the plasma's conductivity which controls the process. Other comparatively short, "over-volted" forms of electrical excitation such as, but not limited to, microwave or RF bursts, may be used as alternatives to or in combination with other pulsing means and/or other sustaining means;

(3) A means of impressing a sub-breakdown voltage of controlled average magnitude or magnitudes. According to the present invention, means of impressing causes current to flow through a region of fluctuating ionization as created by the means for sustaining comprising, for example, the aforementioned pulsing means. Alternatively, a sub-breakdown voltage is magnetically induced as, for example, application of aforementioned square wave energy to maintain an approximately fixed potential through a square wave having alternating polarity. The potential, in either instance, is selected so that E/N falls well below the glow potential and preferably within the range of approximately 7 Td to approximately 10 Td, of course this value is adjustable to account for other system parameters. In preferred embodiments using a controlled "graded" E/N, E/N is continuously varied along the operational path and is a function of $O_2^1\Delta$ concentration (or $O_2^1\Delta$ pressure). Several preferred embodiments of the present invention use graded E/N technology. Grading of E/N over system operation allows for, in most instances, optimum efficiency. As mentioned previously, and with reference to Figure 1, choice of E/N depends on levels of $O_2^1\Delta$, whether measured in terms of concentration or pressure. In particular, $O_2^1\Delta$ levels are monitored (primarily for experimentation) with reference to concentrations and pressures of other chemical species within the system, for example, but not limited to, other oxygen species.

(4) A means of exchanging heat energy is desirable, and in most instances it is required, because the temperature dependence of the pooling rate for $O_2^1\Delta + O_2^1\Delta \rightarrow O_2\Sigma + O_2^3\Sigma$, and the very strong temperature dependence of the equilibrium constant for the excitation reaction $O_2^1\Delta + I \rightarrow O_2^3\Sigma + I^*$. Thus, it is imperative that the process be kept as cold as possible and occur as quickly as possible. Within generators of the present invention, the aforementioned conditions are met by, for example, starting the process very cold, removing the generated heat immediately and by flowing the gas through the apparatus as quickly as possible. Within the lasing volume, fast flow rate and cold temperature conditions are simultaneously met by expanding the flow to supersonic velocities.

10 EXAMPLES

Three specific point design examples of lasers intended for three distinct classes of applications are presented below. All of these examples are based on a linear $O_2^1\Delta$ generator/integral heat exchanger concept as illustrated in Figure 5.

15 Case I System: Open cycle, 20 KW class, continuous laser.

This configuration is intended to provide a very compact, light-weight laser for applications where only short-run times are needed but compact packaging concerns are at a premium. Typical applications for such laser systems include fracturing of rocks in mining or well-drilling operations, where field portability is advantageous. In Figure 8, both side view (top drawing) and top view (bottom drawing) of a Case I System of the present invention are shown. The top view shows only a laser channel, which is common to two other configurations that follow (refer to Figure 8 for other cases).

A laser **800** according to a preferred embodiment of the present invention is shown in Figure 8a. This open cycle electric oxygen iodine laser **800** comprises an oxygen supply **810**, a helium supply **820**, an iodine supply **830**, a power supply system **840**, an $O_2^1\Delta$ electric generator/heat sink assembly **850**, a resonator cavity **860**, a supersonic/subsonic diffuser discharge assembly **870** and a heat exchange system **880**.

As shown in Figure 8, the heat exchange system **880** of this embodiment connects to the oxygen and helium supplies **810, 820**, the $O_2^1\Delta$ electric generator/heat sink assembly **850**, and the supersonic/subsonic diffuser discharge assembly **870**. The heat exchange system **880** further comprises at least one pump for pumping fluid and/or gas **882, 882', 882''**. The at least one pump provides for circulation of fluid/gas from the $O_2^1\Delta$ electric generator/heat sink assembly **850** to the heat exchange system **880**. In this particular embodiment, the heat exchange system **880** further comprises, as shown, a heat exchange loop **884** for exchanging heat with an ejector gas from an ejector gas supply **886**. This sub-assembly optionally comprises, in lieu of or in addition to the heat exchange loop **884**, a thermal energy input **888** to achieve a suitable ejector gas temperature. An ejector gas manifold from the ejector gas supply **886** enters the supersonic/subsonic diffuser at a point upstream **874** from the subsonic portion **876** of the diffuser; however, the ejector gas does not enter the flow stream until approximately the shock region, which is substantially between the supersonic and subsonic regions (as shown more clearly in Figure 8c below).

The $O_2^1\Delta$ electric generator/heat sink assembly **850** of this particular embodiment comprises at least two tubes **852, 852'**. Located at opposite ends of the tubes **852, 852'** are fore and aft electrodes **854, 854'**. This particular embodiment is optionally configured with a fore cathode or anode and an aft anode or cathode, respectively, for purposes of discharging a direct or alternating current at sub-breakdown field strength into the plasma. In either instance, metastable helium is formed at or near the fore electrode, for which the fore electrode comprises a cathode, regardless of whether it comprises a cathode or anode for purposes of providing seed volume ionization from which to initiate an avalanche. Of course for low pressure operation and other types of operation, the invention does not have to rely on this particular apparatus or method of forming metastable helium. Other methods and apparatus for providing seed volume ionization are within the scope of the present invention and known to those of ordinary skill in the art.

The power supply system **840** comprises a floating, high repetition, nanosecond, high voltage pulser **842**, a DC power supply **844**, power conditioning electronics **846**, a high voltage isolated power transformer **848**, a command charger **847** and appropriate leads **843** to the $O_2^1\Delta$ electric

generator/heat sink assembly **850**. The command charger **847** is positioned between the power conditioning electronics **846** and the floating, high repetition, nanosecond, high voltage pulser **842**. The high voltage isolated power transformer **848** is connected to the power conditioning electronics **846**.

5

The laser beam is produced at the resonator **860**, which in this particular embodiment comprises a two-pass unstable resonator cavity, shown in an end view in Figure 8. The resonator **860** is positioned after an iodine injector **832** and before the supersonic diffuser **872**. In this particular embodiment, the iodine injector **832** comprises a supersonic nozzle block, which a particular embodiment thereof is described in further detail below.

10

The iodine injector **832** shown in Figure 8a comprises a supersonic nozzle block. A close-up of this block **900** is shown in Figure 8b. This block comprises an inlet side **902** and an outlet side **904**. Gases in subsonic flow enter the inlet side **902**, mix with iodine, and optionally a combination of helium and iodine, supplied through iodine injection ports **903**, **903'**, in a mixing region **906**, **906'**, **906''**. This mixture of gases expands in the supersonic expansion region **908**, **908'**, **908''** to achieve supersonic flow. In a particular embodiment of the invention, gas leaving the supersonic nozzle block comprises a velocity of approximately Mach 2.5 to approximately Mach 3.0. The gas further optionally comprises a temperature of approximately 112 K or lower. The basic principles of the supersonic nozzle block of Figure 8b are known to those in the art of COIL lasers.

15

20

Figure 8c shows a top view of the inventive apparatus of Figure 8a. In this view of this particular laser embodiment **800**, the oxygen supply **810**, the helium supply **820**, the iodine supply **830**, the $O_2^1\Delta$ electric generator/heat sink assembly **850**, the resonator cavity **860**, and the supersonic/subsonic diffuser discharge assembly **870** are shown. The resonator cavity **860** further comprises a plurality of resonator mirrors **862**, **862'**, **862''**, **862'''**. The resonator cavity additionally comprises at least one laser beam output coupler **864**. This mirror optionally comprises an annulus for output of an annular laser beam, if used in conjunction with an unstable resonator, or a partially transmitting and partially reflecting optical element, if used in conjunction with a stable resonator.

25

In a Case I System, all laser gases pass through the channel only once (open cycle) and must be stored in a quantity sufficient to cover a particular application or mission. Storage of gases in cryogenic form provides a means of cooling, or exchanging heat energy, with the system and, in turn, heat energy absorbed into cryogen causes a change to a gaseous state and vaporization.

In a Case I System, a $O_2^1\Delta$ generator of the present invention consisting of, for example, but not limited to, approximately 80 tubes, each approximately 42 cm long (longer tubes, for example, but not limited to approximately one meter in length or longer are also within the scope of the present invention), produces an oxygen flow rate that is sufficient to power a 20 KW laser. The generator, in turn, comprises a pre-ionization means and a means for sustaining quasi-continuous ionization by the same kind of pulsers and power supplies described for the 2 tube experimental generator of Figure 5. The physical operating conditions for this laser are summarized below.

Physical Operating Conditions for 20 KW Electric Oxygen Iodine Laser

Minimum Yield (Y) = 0.16, $T_{cav} = 112$ K Case

Resonator:

$\alpha_o = 0.0074$, $Mag = 1.4$ Resonator, $L = 3$ meters total path

Scaled from ROTOCOIL according to: $\alpha_o \approx \left(1 - \left(\frac{1}{2K_{eq} + 1}\right)\left(\frac{1}{Y}\right)\right)$

Lumped Mirror Losses: $r_1, r_2 = 0.998$, $|\gamma|_{max}^2 = 1 - \delta \cong 0.75$

$$\eta_{ext} = \eta_o \eta_s = \frac{\ln(|\gamma|^2 r_1 r_2)}{2\langle\alpha_o L\rangle} + 1 + (2 - r_1 - r_2) \times \left[\frac{1}{\langle 2\alpha_o L \rangle} + \frac{1}{\ln(|\gamma|^2 r_1 r_2)} \right] = 0.92$$

Kinetics:

$$\eta_{kin} = \frac{Y - \left(\frac{1}{2K_{eq} + 1}\right)}{Y} = 0.888$$

where:

$$K_{eq} = 0.75 \times e^{402/112} = 27.16$$

$$Y = \frac{|O_2^1\Delta|}{|O_2^1\Delta| + |O_2^3\Sigma|} = 0.16$$

5

Power Output = 20 KW

$$\begin{aligned} \text{Power Available} &= P_{out} / (\eta_o \eta_s \eta_{pack} \times \eta_{kin}) \\ &= 20 \text{ KW} / (0.92 \times 0.9 \times 0.888) = 27.2 \text{ KW Stored Power} \end{aligned}$$

10

$$P_{stored} = \dot{M}_{(moles/sec)} \times \left(Y - \left(\frac{1}{2K_{eq} + 1} \right) \right) \times 91.3 \text{ KJ/mole}$$

$$\dot{M} = \frac{27.2 \text{ KW}_{stored}}{(0.16 - 0.018) \times 91.3 \text{ KJ/mole}} \cong 2.1 \text{ moles/sec}$$

15

Summary of 20 KW Laser

Input Parameters:

M = 2.5 Flow

$T_{cav} = 112 \text{ K}$

$K_{eq} = 27.16$

20

$\dot{M} \cong 2.1 \text{ mole/s } O_2 \text{ (+ 2.1mole/s He + 0.02 - 0.04 mole/s I}_2\text{)}$

$P_{gen} \cong 25 \text{ Torr } O_2 + 25 \text{ Torr He}$

$P_{cav} \cong 5 \text{ Torr, Total}$

$Y = 0.16, \text{ fraction } O_2^1\Sigma = 0.018$

Output Parameters:

25

Power Out = 20 KW

$P_{stored} = 27.2 \text{ KW}$

$\eta_{next} \cong 0.92$

$\eta_{pack} \cong 0.9 \text{ (assumed)}$

$\eta_{kin} \cong 0.888$

$\alpha_o \cong 0.0072$

Mag 1.4 Res approximately 2 times diffusion limit

Power Requirements

I. Power Required to Drive Laser

	Plasma Ionization	28 KW
5	Electric Pump Excitation	140 KW
	Gas Re-Circulation	20 KW
	Auxiliary Systems	40 KW
	Power Conditioning Losses (includes electrode losses)	<u>26 KW</u>
	Laser Power Requirements, subtotal*	254 KW
10	Laser Wall Plug Efficiency (less cooling subsystems)	8%

II. Power Required to Reject Heat For Closed Cycle Operation (if electrically refrigerated)

	Power Added to Reject 40 KW at +20°C	40 KW
	Power Added to Reject 114 KW at -20°C	<u>130 KW</u>
15	Thermal Management Subtotal	170 KW
	Total System wall Plug efficiency (electrically refrigerated)	4.7%

* Assumes worst case performance estimates, and that all heat is exhausted into ambient air (no "cooling tower"). Specifically assumes:

20	Fraction $O_2'\Delta$ generated	17.8%
	Fraction $O_2'\Delta$ lost to cooling	1.8%
	Fraction $O_2'\Delta$ reaching output of generator	16%
	Efficiency of $O_2'\Delta$ generation at 10.5% concentration	22%
	Total kinetic energy in flow stream	30 KW
25	Pump power needed to generate 30 KW excited species	140 KW

Note that "II. Power Required to Reject Heat for Closed Cycle Operation" is also useful in describing open-cycle operation, wherein dynamic gas expansion from a source to the generator and/or cryogenics are optionally used to maintain temperature.

Note that all of the numbers and calculations shown are for illustration of various embodiments of the present invention and do not limit the scope of the invention.

5 As shown, subsequent to the oxygen plus helium (or, e.g., argon) buffer gas passing through the $O_2^1\Delta$'s generator structure, iodine vapor carried by a buffer gas (e.g., helium) is injected into the flow channel. Immediately past the mixing region, the flowstream is expanded to a flow velocity of Mach 2.5 where cooling occurs, to approximately 112 K at the resonator. The cavity is 1 m wide, utilizes a 2 pass transverse unstable resonator, which produces a 2 times diffraction-limited beam at
10 approximately 20 KW. About 200 KW of electrical power is supplied to the system, and approximately 2.1 moles O_2 plus approximately 2.1 moles He are stored for each second of operation.

Although design calculations were based on 20 KW operation, the technology of a Case I System is scalable up or down as needed. In fact, the results presented above were based on $O_2^1\Delta$
15 yield measurements that are approximately a factor of two less than a realistically achievable, optimal yield. Therefore, a most optimistic scenario achieves 40 KW average power output from the same Case I System without need for further power input.

Case II System: 20 KW average power-class, closed-cycle, continuously operational laser.

20 This system employs the same basic cavity and operational specifications as a Case I System, except that it operates (nearly) closed cycle, so that laser gas make-up rates are relatively inconsequential. This responds to the requirements for a typical heavy-metal working industrial laser and results in a package which very closely resembles a 20 KW, CO_2 laser in terms of efficiency gas make-up and cost per watt; however, a Case II System of the present invention makes much narrower
25 cuts, can cut up to ten times deeper, and nearly ten times faster than its CO_2 laser counterpart. Figure 9 illustrates an embodiment of a Case II System showing how the gas flow loop is nearly closed.

Case II laser systems are truck-mountable and field operational, thereby enabling the disassembly of 12 inch-thick steel nuclear reactor vessels and centrifuges for which the U.S. Department of Energy has a most pressing need. Ships, tanks, and many other heavy manufacture operations are foreseen target users of Case II System embodiments of the present invention.

5

Referring to Figure 9, a closed-cycle embodiment of a laser system **920** of the present invention is shown. This laser system **920** comprises a generator/heat exchanger **922**; a power supply system **924** that comprises a floating, nanosecond, high voltage pulser and a DC power supply; a gas return flow loop **930** and an iodine vapor-He return loop **950**. The gas return flow loop **930** further comprises at least two heat exchangers **932**, **932'** (optionally comprising a chiller, see element **932'**); a roots blower **934**; a slow flush vacuum pump **936**; and a make-up oxygen supply **938**. The iodine vapor-He return loop **950** further comprises a helium supply **952** and a heat exchanger **954** that optionally comprises a heater.

Referring again to Figure 9, a Roots blower pump **934** is used to recompress gases emerging from the subsonic diffuser **960**, after which the heat introduced by the pump is removed by a heat exchanger **932'**, and the flowstream is reintroduced to the electric $O_2^1\Delta$ generator **922**. This particular Case II System resembles a CO_2 laser system; however, with a unique need for handling recycle of iodine **950**. In a preferred embodiment of a Case II System, iodine vapor (carried by heated helium) must be injected just upstream of the supersonic nozzles **956** and removed from the flowstream before the flow reenters the $O_2^1\Delta$ generator **922**. Hence, this particular Case II System requires two separate flow loops **930**, **950**, one for the bulk of the gas and another for a relatively small amount of iodine (amounting to approximately less than 1% of the net flowstream). Where buffer gas is used, the gas comprises oxygen species, buffer (e.g., He and/or Ar) and iodine species.

25

In the aforementioned Case II System, gaseous iodine is "frozen out" on a cooled structure, i.e., a condenser/heat exchanger, **932'** downstream of the subsonic diffuser **960**, as illustrated in Figure 9. Solid state iodine resides in crystalline form solidified on the condenser's **932'** extensive surface area. After a period of time, for example, a few hours operation, the condenser's

surface becomes saturated. The saturated condenser surface is then moved into a second position 954 where it is heated thereby subliming and liberating the solidified I₂ as vapor, which, in turn, re-enters the mixing nozzles. In preferred embodiments of a Case II System, there are at least two identical condensers 932', 954, at least one for condensing I₂ vapor from the system 932' and at least one for subliming I₂ solid for re-entry to the system 954 as vapor. As shown in Figure 9, interchange of surfaces and/or condenser structures requires a downtime of, for example, a few minutes, every several hours; however, the interchange operation is fully automatable.

Case II Systems, as noted for CO₂ laser systems, do not operate as a completely closed-cycle: some exchange of gas is required. For Case II Systems, heated helium gas 952 must be injected to carry the iodine and a correspondingly small amount of laser gas must be pumped out of the system. This process disturbs the helium/oxygen ratio thereby requiring introduction of additional "make-up" oxygen 938 to maintain a proper balance. Hence, the system is not completely closed, but the make-up rates are tolerable and practical for the aforementioned applications.

In addition to powering the Roots blower 934, a formidable amount of energy must be spent to cool the O₂¹Δ generator 922. The power drain attributable to cooling is comparatively negligible because the laser per se is very efficient. For example, refer to the numbers presented in Figure 7 and above as indicators of the comparative power requirements. Calculations for Case II Systems indicate that an overall efficiency of 5% is achievable -- an efficiency comparable to that of a CO₂ laser system when one accounts for the costs of gas circulation, laser cooling, chilled water requirements, etc.

Case III: High repetition, pulsed, 150 KW average power, approximately 200 joules/pulse (200 megawatts peak), closed-cycle laser.

This particular embodiment of the present invention is intended to address applications such as, but not limited to: (1) nudging space debris out of orbit so that it burns up in the atmosphere; or nudging comets or asteroids repeatedly to gradually divert their path so that they miss striking the

earth. Scaled-up Case III laser systems could also play a role in generating controlled nuclear fusion power or propelling rockets and/or satellites into space.

For purposes of this discussion, the calculated parameters for a Case III System appear below.

150 KW Ave., 200 J/Pulse Closed Cycle Electric Oxygen Iodine Laser

Minimum Yield (Y) = 0.16 (assumed), Cavity Mach = 2.5, $T_{cav} = 100$ K Case

Resonator:

$\alpha_o = 0.002, I_{sat} \cong 1440 \text{ W/cm}^2, L = 600 \text{ cm, folded, Mag} = 1.4$ Resonator

α_o scaled from ROTOCOIL data according to:

$$\alpha_o \approx \left(1 - \left(\frac{1}{2K_{eq}} \right) \times \left(\frac{|O_2^3\Sigma|}{|O_2^1\Delta|} \right) \right) \frac{Y}{Y_{RC}}$$

I_{sat} scaled from ROTOCOIL data, according to $I_s \approx \rho V_{cav}$

Lumped Mirror Losses: $r_1, r_2 = 0.998, |\gamma|_{max}^2 = 1 - \delta \approx 0.75;$

$$\eta_{ext} = \eta_{opt} \eta_{sat} = 1 + \frac{\ln(|\gamma|^2 r_1 r_2)}{2\langle \alpha_o L \rangle} + (2 - r_1 - r_2) \times \left[\frac{1}{\langle 2\alpha_o L \rangle} + \frac{1}{\ln(|\gamma|^2 r_1 r_2)} \right] = 0.87$$

Kinetics:

$$\eta_{kin} = 1 - \left(\frac{1}{\left(\frac{O_2^1\Delta}{O_2^{total} - O_2^1\Sigma} \right) (2K_{eq} + 1)} \right) = 0.90$$

where:

$$K_{eq} = 0.75e^{\frac{402}{T_x}} = 31, T_c = 108K$$

Continuous Wave Power Available from Flowstream equals:

$$\dot{M} \left(Y - \left(\frac{O_2 \text{ total} - O_2^1 \Sigma}{O_2 \text{ tot}} \right) \times \left(\frac{1}{2K_{eq} + 1} \right) \right) \times 91.7 = 430 \text{ KW}$$

Sanity Check: $\iiint \alpha_o I_{sat} dV = 696 \text{ KW}$ (deviation probably due to scaling of I_{sat}).

5 Energy per pulse out =

$$(334 \text{ J/pulse}) \times (\eta_{opt} \eta_{sat}) \times \eta_{kin} \times \eta_{kin} = 334 \times (0.87) \times 0.9 \times 0.9 = 235 \text{ J/pulse}$$

Number Cavity Exchange Rate = 1290

Maximum Available Power Out = 300 KW

10 Practical Available Power:

for 2 exchanges per pulse - 650 pps = 153 KW

for 3 exchanges per pulse - 430 pps = 100 KW

Power Requirements: (33% Duty Cycle)

	Electrical Efficiency of Generator	20%
15	Pooling Loss, Efficiency	90%
	Threshold Efficiency	90%
	Energy in Flow (100% Duty)	430 KW
	Pump Power	700 KW
	Continuous Avalanche Pre-ionization	100 KW
20	Cathode/Anode Loss	15 KW
	Auxiliary Systems	33 KW
	Prime Mover	380 KW
	Refrigeration	700 KW
	Power Conditioning	<u>200 KW</u>
25	Total	2128 KW

Prime Mover/Gas Requirements:

approximately 400,000 CFM

10 Torr Inlet

30 $\delta P = 10 \text{ Torr}$

O₂ Flow: 32 moles/s

He Flow: 32 moles /s

Make up:

- 5 Plug Efficiency at 3 exchange/pulse: $100/2128 = 4.7\%$

In particular, the feasibility of extracting giant pulses at a sufficient rep rate to enable the aforementioned types of applications is demonstrated.

- 10 A preferred embodiment of a Case III System comprises a closed-cycle, supersonically flowing, cavity configuration incorporating transverse optical extraction from an "unstable resonator." This embodiment comprises continuous pumping from a linear integral heat exchanger O₂¹Δ generator, followed by iodine vapor (plus, e.g., buffer) injection -- then supersonic expansion. Lasing is retarded while excited gas fills the cavity by means of applying a "permanent" magnetic field that
- 15 causes Zeeman-splitting of laser transitions states. Once the cavity is filled and acoustical disturbances have settled out, at least one Helmholtz coil is electrically pulsed to nullify the permanent magnetic field. Through pulsed nullification of the permanent field and the resulting formation of spontaneous noise, the resonator builds a laser beam within several microseconds. Alternatively, a regenerative amplifier replaces the aforementioned unstable resonator. If pre-seeded from a local
- 20 oscillator, this alternative system will provide much shorter pulses. Gordon D. Hager at Phillips Laboratory, Kirtland Air Force Base, USA, has reduced the Zeeman splitting method of Q-switching to practice. See, e.g., "Demonstration of a repetitively pulsed magnetically gain-switched chemical oxygen iodine laser," Hager et al., Chem. Phys. Letters., Vol. 204, No. 5, 6, pp. 420 - 429 (1993). The Zeeman splitting and Q-switching methods and apparatuses of Hager are hereby incorporated by
- 25 reference.

There are some particular constraints that are driven by the nature of the technology, and the nature of the mission. For example, the laser's cavity must operate at low temperatures, for example, approximately 100 K is a preferred operating temperature, and the cost of conventional refrigeration

reduces overall economy. Hence, supersonic flow provides the most practical way of reducing the cavity temperature. Also, hundreds of joules (perhaps kilojoules) must be extracted in each pulse, so the cavity must be large enough to store this energy. A large cavity combined with supersonic flow translates to seemingly high volumetric flow rates (approximately 480,000 CFM for the case presented); however, the pressure is low and therefore the prime-mover power amounts to a much smaller fraction of the total system power than normally encountered with high average power lasers; i.e., only 10% of the total system power is consumed by the prime mover for this "strawman" design if it were to run either CW or at full average power in the pulsed mode. Acoustic settling times may preclude pulsing the flow once per cavity exchange (which would deliver 225 KW average); however, operating at 2 to 3 cavity exchanges per pulse maintains an overall efficiency as high as approximately 5.5% or 4.5%, respectively. Under such circumstances, 230 joule pulses are extractable from the particular cavity analyzed.

Naturally, if the system is to operate continuously at a repetition rate falling between 430 and 660 pps, closed-cycle operation is greatly preferred. And for closed-cycle operation, the most severe energy penalty becomes the matter of removing waste heat. Half of the waste heat (approximately 1 MW) is efficiently carried off by water at room temperature, but an additional approximately 1 MW must be removed at reduced temperatures (-30°F). Removal of additional waste heat will cost at a minimum 1 MW of electric power to drive, for example, a refrigerative heat exchanger. The remaining thermal task — that of maintaining approximately 110°K within the cavity — is accomplished by supersonic expansion. This thermal energy burden, in addition to the prime-mover power requirements, was included in the derivation of the 5% wall plug efficiency factor. Again, in terms of efficiency, the systems of the present invention rival CO₂ laser systems.

Regarding yield, or fraction of O₂¹Δ achievable by the lab generator used in several of the aforementioned examples: Lab measurements indicate a yield of at least approximately 16% -- the "strawman" design and calculations are based on this value. Theoretically, more than twice this yield is expected (i.e., approximately 32%), and in fact, high yields were measured on several occasions; however, these higher values were not measured repeatedly with statistical accuracy in mind.

Additionally, a known artifact in lower measurements accounts for the possible anomaly of low yield measurements. Therefore, operation of the present invention can conservatively provide yields of at least 16%. Ultimately, higher yields will have a very positive impact in many ways, resulting in: a smaller system size; a higher pulse energy; a shorter cavity resonator for a given power level (owing to higher gain); a higher efficiency; less severe refrigeration/cooling requirements; and potentially subsonic operation for certain missions.

The aforementioned "strawman" designs assume that generator pressure is doubled over the levels demonstrated because it is theoretically and potentially achievable. If not achievable, the pulsed energy storage is halved. On the other hand, if the generator pressure is doubled again (which is quite probable), the pulse energy density doubles.

Finally, the prime-mover power requirement was based on an assumed diffuser recovery factor of 50%. Because there is a small, but yet unquantified, heat release in the supersonic flowstream due to the thermalization of energy stored in $O_2^1\Sigma$, the diffuser operation is potentially adversely affected. This may potentially double the prime-mover power requirement resulting in an overall efficiency reduction from approximately 5% to approximately 4%.

Pulser Circuits and Generator Examples

Specifically it is the function of the "controlled avalanche" or pulser circuit to provide and sustain a quasi-continuous level of ionization within the $O_2^1\Delta$ generator needed to conduct current during the off periods between the pulses it generates. Regarding ionization, information disclosed in "Continuous Uniform Excitation of Medium Pressure CO_2 Laser Plasma by Means of Controlled Avalanche Ionization," Alan Hill, Applied Phys. Letters 22(12), 15 June 1973 is relevant to this point; however, such technology was not previously applied to generation of atomically excited molecular species. This article is incorporated herein by reference. This current, in turn, is driven by the application of a second, DC potential (or equivalent) whose magnitude is of a specified value falling well below that value needed to contribute to the ionization process.

In addition to providing a continuous stream of pulses that sustain ionization, it may also provide an associated string of pulses used to generate pre-ionization or equivalently meta-stable helium in chambers that lie upstream of the main discharge sections. Such pre-ionization would float on top of the primary "controlled avalanche" pulses, with the controlled avalanche pulses perhaps
5 being delayed slightly with respect to the pre-ionization pulses. (There are a number of methods, previously outlined, for generating the pre-ionization.)

For the case of the preferred embodiment, the controlled avalanche pulser – together with its pre-ionization complement – floats on top of a pure DC potential whose function is to provide the
10 pump current under a temporally steady (although perhaps spatially graded) electric field of the order $E/N = 10 \text{ Td}$.

Finally it is the function of either this pulser or an associated pulser to provide a single, giant pulse at turn-on in order to produce the ultimate, quasi-steady-state level within a few pulse periods.
15 This one-time intermediate "jump start" process negates the need to supply every pulse at an E/N value of approximately 180 Td. Instead, we provide only the fast pulse at the value of approximately 180 Td, then allow the quasi-continuous pulser circuit to settle down to its ionization maintenance level, which under the conditions of residual ionization (at its start) most probably falls between the value $E/N = 80 \text{ Td}$ and $E/N = 120 \text{ Td}$ (depending on the design level of electron number density,
20 ionization rep rate, pressure, and gas mixture).

The pulser's circuit is designed to interact with the plasma's conductivity, such that its applied potential falls below the value of E/N required to sustain an avalanche as the peak sustained current (correspondingly the electron number density) reaches its design level. Thus, the controlled
25 avalanche pulse potential across the discharge falls well below its impedance-matched potential value in a time much shorter than its impedance-matched, pulse-forming network's time period, as a result of the load impedance having fallen well below the network's impedance at the design point of peak plasma conductivity.

The specific requirements of the controlled avalanche pulser are:

5 (1) To provide a pulse sequence, wherein each pulse rises to an E/N value of ~180 Td under open circuit conditions (at 50 Torr-Amagat discharge conditions, the corresponding potential may typically reach 180 KW).

(2) Under residual ionization conditions, where the ionization level has decayed to its minimum value following the off period of the pulser and at the onset of the next pulse, the E/N value is clamped to a value of ~80 Td to ~120 Td (according to adjustment of circuit parameters).

10 (3) Upon completion of the avalanche needed to restore lost ionization to maintain the correct mean level of ionization, the E/N value must, by interaction with the current, have fallen to a level insufficient to contribute to further ionization – typically less than 40 Td.

(4) The rise time of the controlled avalanche pulse is less than 30 nanoseconds, but preferably less than 15 nanoseconds, and most preferably less than 5 nanoseconds.

15 (5) The impedance-matched pulse period is to be less than 75 nanoseconds, but preferably less than 30 nanoseconds, and most preferably less than 15 nanoseconds, provided that the rise time can be achieved on the order of 5 nanoseconds.

(6) The "jump start" pulse should be capable of sustaining current flow at the voltage corresponding to a plasma E/N of ~150 Td to ~180 Td or more, and at a current level characteristic of the controlled avalanche pulser impedance operating into a matched impedance load.

20 (7) The rep rate is to be adjustable and must equal or exceed 20,000 pulses per second continuously, and the pulses must be triggerable on demand.

However, in order to excite the highest density flow stream which may reach 150 Torr-Amagat for the case of ionizing very high-powered lasers, the method may require pulsing at higher repetition rates than may be derived by a single controlled avalanche pulser. This is because the ionization loss rate increases with increasing density. In such cases, the rep rate obtainable from a single pulser may be doubled, tripled, or even quadrupled to as much as 100,000 pulses per second, simply by interleaving the pulses from 2, 3, or 4 modules which individually operate at 20,000 to 25,000 pulses per second and function according to the aforementioned specifications. Each of the units must be

appropriately synchronized and time-delayed with regard to each other. Then, the 2, 3, or 4 individual pulse trains are simply added.

Example of Pulser Circuit

5 The design of a controlled avalanche circuit depends on, for example, the power range of a particular laser. The example presented below is suitable for an approximately 20 KW continuous power laser. In general, the design principles of this example are suitable for lasers of average power falling between approximately 5 KW and approximately 150 KW.

10 Figure 10 illustrates a controlled avalanche, or "pulser," circuit in schematic form. For purpose of illustration, circuit connections are shown as lines or wires. In actual circuits, high speed, impedance-matched mechanical structures such as, but not limited to, coaxial cylinders, strip lines, or wave-guides are used. An actual packaged circuit as represented by the schematic of Figure 10, therefore, may physically resemble the circuit shown in Figure 11, a description of this figure follows
15 below.

Referring to Figure 10, the pulser circuit and $O_2^1\Delta$ plasma generator are illustrated together, since in practice the two units are inseparable and do interact to form a unified circuit. As shown, the pulser circuit sits on top of the DC power supply **1001**, which provides the excitation power at a
20 potential which maintains temporally constant, but perhaps spatially graded plasma conditions at or near a value of E/N of approximately 10 Td. A large capacitor **1002** is used to stabilize voltage conditions during a fluctuating current load, and to bypass the avalanche pulses, thus referencing these to ground potential. Typically, the required pump potential will fall between approximately 7 KV and approximately 20 KV, depending on gas density and generator tube length.

25

The pulse forming network of the circuit consists of four sets of stacked cable Blumlein lines **1011**, and are wired so that their potentials add at the output end. A fifth set of cables form a final Blumlein line whose potential is added onto the top of the first four lines **1012**. The first four stacked lines provide the primary pulse train which maintains ionization while the fifth line powers the helium

meta-stable generators which are located upstream of the $O_2^1\Delta$ generator plasma tubes, and serve to provide a volume-distributed source of initial pre-ionization.

For the case of a 20 KW class laser, each of the five lines consist of two approximately 50 ohm coaxial cables, such that their switched impedance on the front end is approximately 5 ohms. If the line has been charged to approximately 20 KV, then approximately 4 KA will flow through the thyatron switch **1003**. In turn, the four line segment will have an output impedance of approximately 400 ohms, thus generating an approximately 200 amp pulse at approximately -80 KV if the load were matched to the line at 400 ohms. Note, however, that in the absence of ionization, the output voltage doubles to approximately -160 KV at zero current. The fifth line provides approximately 200 amps at approximately -20 KV lying on top of the approximately -80 KV primary output in addition to the DC pump potential (perhaps -10 KV) in the case where both circuits are loaded into their matched impedances: approximately 400 ohms and approximately 100 ohms, respectively.

When impedance-matched, the pulse output is a square wave whose pulse width matches the two-way propagation time through a single cable. For example, approximately 30 nanosecond wide pulses will be produced when the cable lengths (individually) are cut to be approximately 10.6 feet long, where the cable's index of refraction is assumed to be approximately 1.4 – the value which is characteristic of a 50 ohm cable.

20

In order for the Blumlein lines to function as intended, they must be discharged by the thyatron during a time period which is short compared to the line's two-way pulse propagation length. This is accomplished by using an ultra-fast (pre-ionized), low-inductance thyatron **1103** in combination with a METGLAS® saturable magnetic switch core **1113**, and by using an impedance-matched current distribution structure. This switch is for simultaneously grounding the front ends of the Blumlein lines to launch pulses, each time the front ends are grounded one pulse is launched. The METGLAS® core may be reset between pulse firings by means of a floating DC bias current winding on the core.

The basic sequence is to pulse-charge all of the cables from a high voltage power supply **1106** through a triggered command charge circuit consisting of a vacuum tube **1107** and an inductor **1108** which transfers the charge in a time period defined by approximately the resonant half period of the reactor's inductance and the cable's net total capacitance. The tube **1107** also prevents the cable's charge from flowing backward, since the resonant transferred voltage is nearly double that of the charging supply. Note that when the positively charged cable Blumlein lines are switched to ground at the input, a negative high voltage pulse is produced at the output.

Both thyatron and vacuum tubes are controllable by electronic circuits, which are schematically represented by boxes **1104** and **1109**, respectively, and which are powerable by floating isolation transformers **1105** and **1110**, respectively.

The following describes how the outputs of the cable Blumlein lines are distributed to the array of plasma tubes and their meta-stable helium injection pre-ionizing sections, and also the means by which excess energy is discarded to allow rapid fall time. In general output ends of the Blumlein lines are connected serially. Before continuing this description, however, elaboration of a few details is helpful. The last cable comprising the fifth Blumlein line section is shunted across its output through inductor **1115** in order to remove residual charge prior to pulse charging it (otherwise the line would float). Next, a short length **1116** extension has been added to the output of the ionization pulse line in order to delay the main generator tube's excitation with respect to the pre-ionization.

Finally, the entire string of pulse cables are shunted with a second saturable reactor magnetic switch into a large capacitor, which in turn discharges into a resistor **1114**, this is also referred to as a snubber circuit. The magnetic switch holds off conduction for a specified time period, then dumps residual energy (which may be bouncing around due to imperfect impedance matches). This allows the applied potentials to fall in direct response to the plasma, thus circumventing an elevated potential to exist beyond its desired point in time. Again, the saturable magnetic switch must be reset between pulses by means applying a DC bias current to the METGLAS® core.

A number of pulsed ground potential connections must be distributed throughout the generator plasma array to enable low inductance current return. These are each passed through blocking capacitors **1124** in order to ground the pulses while blocking the DC potential, above which the pulse network must float.

5

A single pulse module comprising ten cables, and one thyatron switch can power as many as, for example, but not limited to, 80 plasma tube generators with their meta-stable pre-ionizer sections. In this particular example, each tube-pre-ionizer assembly consists of a BeO or Al₂O₃ tube **1122**, an anode/input nozzle **1121**, an oxygen and helium reservoir **1117** into which all of the oxygen and most of the helium is introduced, a metal tube **1118** into which some helium (and/or optionally argon is introduced), an anode **1123**, and an auxiliary electrode (or electrodes) **1125**, which is used to jump-start the ionization process and possible to help grade the DC pump potential.

The pre-ionization potential is applied between the metal helium injection tube **1118** and the cathode **1121** to provide the pre-ionization pulses. Note that the main discharge cathode serves as an anode for the pre-ionization pulse (the inside of the helium injector tube forms a hot cathode space charge layer which serves to generate meta-stable helium).

The two pulse output busses, residing for example at about -160 KV open circuit and -180 KV open circuit, respectively, are distributed to the tubes through isolating/ballasting inductors **1119** and **1120**, one for each of the two circuits and for each tube.

Finally, the intermediate electrodes **1125** are connected through ballasting inductors **1126** (one for each tube) to the jump-start pulser. This pulser provides upon start-up, only one low impedance pulse at a positive polarity which is opposite from the upstream negative polarity. The two potentials are additive (for example, -180 KV + 50 K) over a fraction of the tube's total length, thus facilitating rapid initial breakdown.

Referring again to Figure 11, referenced above, a controlled avalanche circuit mechanical assembly **1200** is shown. A transmission line **1202** is shown centrally surrounded by cable Blumlein lines **1204, 1204'**. A thyatron **1206** is shown centrally connected to the transmission line **1202** and in connection with floating thyatron control electronics **1208**. A current return **1210** is also shown.

5

Referring to Figure 12, an alternative means **1300** of floating a DC potential on top of a DC jump potential and the pulsed high voltage avalanche ionization potential is shown. Compare to the fifth set of cables that form a final Blumlein line whose potential is added onto the top of the first four lines **1012**, as shown in Figure 10. The alternative means **1300** comprises a high voltage blocking inductor **1302**, for example, wound from coaxial cable, that is connected through a resistive device **1303** to the helium supply inlet **1304** that feeds a generator tube **1306**. An oxygen and/or inert gas supply inlet is also shown **1308**. Also shown in Figure 12 is a high voltage pulser **1310**, a DC supply **1312**, and a source of DC pre-ionization voltage **1314**. Electrodes **1316, 1316'** of the generator tube **1306** are shown bounding at the ends, of course, the electrodes may number more than two per tube and be located at a variety of points along the tube.

10
15

Longitudinal Beam in Supersonic Throat Arrangement

The present invention also includes a laser comprising a gas, a beam produced by the gas and a throat wherein the gas and beam pass through the throat. In one embodiment, the throat comprises a converging region and a diverging region to achieve supersonic flow of gas passing therethrough. A laser according to this gas flow / beam arrangement embodiment **1400** is shown in Figure 13 (e.g., an axial cross-section through a substantially cylindrical structure). Lasers according to this embodiment are optionally suitable for power outputs of approximately 5 to approximately 20 kW. According to this embodiment, a beam **1402** passes through a gas flow throat **1404**. As described in other embodiments herein, this laser **1400** is capable of either closed or open cycle operation and comprises some features of, for example, the laser apparatus shown in Figures 8a and 8c. For instance, as shown in Figure 13, this embodiment comprises at least two oxygen supply ports **1424, 1424'**, at least two helium supply ports **1428, 1428'**, at least two iodine supply ports **1432, 1432'**, an $O_2^1\Delta$ electric generator/heat sink assembly **1450**, and a resonator cavity **1460**. Of course,

20
25

embodiments comprising a single supply port for oxygen, a single supply port for helium, and/or a single supply port for iodine are within the scope of the present invention, as are headers and/or other distributors for the same. According to one embodiment, oxygen and iodine are supplied at a ratio of approximately 50 to 1. Adjustments to the oxygen to iodine ratio are useful for controlling gain.

5

The $O_2^{1\Delta}$ electric generator/heat sink assembly **1450** of this particular embodiment comprises at least two tubes **1452, 1452'**. Each tube is surrounded by a heat sink or heat exchanger, which optionally provides for flow of a coolant or heat exchange fluid (including gas), as indicated by coolant inlets **1456, 1456'** and outlets **1458, 1458'**. Of course, the inlets may optionally serve as outlets and vice versa. While the tubes shown in Figure 13 are substantially parallel to the beam, embodiments comprising tubes that are arranged at other angles with respect to the beam are also within the scope of the present invention. An embodiment comprising at least one annular region that provides for carrying oxygen and/or helium gas is also within the scope of the present invention and a heat sink and/or a heat exchanger for use in such an embodiment optionally comprises an annular cross-section. Further while iodine inlets **1432, 1432'** are shown in Figure 13 positioned perpendicular to the beam axis, an inlet or a plurality of inlets are optionally positioned parallel to the beam axis or at any angle to the beam axis. While not limiting, it is preferred that iodine enters and mixes the gas prior to the throat **1404**.

10

15

20

Based on the discussion of other embodiments presented herein (e.g., see discussion of Figure 8), one of ordinary skill in the art would understand that the embodiment shown in Figure 13 also comprises a power supply and electrodes. Of course for low pressure operation and other types of operation, the invention does not have to rely on this particular apparatus or method of forming metastable helium. Other methods and apparatus for providing seed volume ionization are within the scope of the present invention and known to those of ordinary skill in the art.

25

The laser beam of the embodiment shown in Figure 13 is produced in the resonator cavity **1460**. Gases in subsonic flow, mixed with iodine, enter the inlet side of the throat **1404**. This mixture of gases expands in the supersonic expansion region of the resonator cavity to achieve supersonic

flow. In a particular embodiment of the invention, gas leaving the throat comprises a velocity of approximately Mach 2.5 to approximately Mach 3. The gas further optionally comprises a temperature of approximately 112 K or lower and/or experiences a pressure drop of approximately one order of magnitude.

5

While the arrangement shown in Figure 13 comprises a single beam **1402** that passes through a single gas flow throat **1404** alternative arrangements comprising a plurality of throats and/or a plurality of beams are within the scope of the present invention. In general, the beam diameter **1402** is substantially matched to the diameter of the throat **1404**. In the embodiment shown in Figure 13, the beam **1402** is bound by two mirrors **1412**, **1416**. One of the mirrors, for example, but not limited to, the left mirror **1416**, comprises a partially reflective surface that allows for partial transmission of the beam **1402**. Of course, the other mirror **1412** optionally comprises properties that allow for transmission to form, for example, a dual beam apparatus. Alternatively, the left mirror **1416** does not allow for transmission and the right mirror beam is partially reflective. This embodiment further optionally comprises an unstable resonator, for example, but not limited to, a system wherein at least one mirror comprises an annulus for output of an annular beam.

Referring to Figure 14, a diagram of a beam **1402** is shown. Note that the beam diameter increases from the throat **1404** to the right mirror **1412**. Also note that the right mirror **1412** comprises a concave surface. The surface is concave to account for changes in the phase front (see dotted line near right mirror **1412**) -- in most instances, the phase front at the throat is substantially flat (see dotted line near throat **1404**). Of course, compound elements are optionally used at either end to correct for phase front distortions and/or to focus the beam.

According to one embodiment, the length is sufficient to extract approximately 5% of the energy from the excited gas. The embodiment shown in Figures 13 and 14 is generally applicable to any transfer type laser. More specifically, such an beam/cavity arrangement is useful when kinetics allow for the lasing molecule to be recycled many times over the length of the cavity. For example, a transfer molecule (e.g., but not limited to, iodine) may be energized and lased from approximately 10

times to approximately 100 times over the length of the cavity. This allows for gain and, again, is controllable by, for example, adjusting the ratio of lasing molecule to non-lasing molecule(s) in the gas. In one embodiment, the cavity comprises a length from approximately 0.1 to approximately 2 meters.

5 The throat **1404** of the embodiment shown in Figure 13 has, for example, characteristics that allow for a particular mass flow rate. Such a throat optionally comprises an upstream converging region and a downstream diverging region. Characteristics of converging, throat and/or diverging regions are useful for providing a particular Mach number, for example, but not limited to, Mach number of approximately 2 to approximately 3. As shown in Figure 13, the resonator cavity expansion
10 region (from throat **1404** to right mirror **1412**) comprises an increasing cross-section. The increasing cross-section helps to account for boundary layer growth, which, in turn, helps to reduce shocking down of the gas in the cavity. While shocking down of the gas in the cavity may be tolerated, in most instances, shockdown occurs in a region removed from the beam path. For example, referring to Figure 13, shockdown occurs in, or proximate to, a substantially annular region **1420** adjacent to a
15 diffuser structure **1408** that comprises part of a subsonic diffuser. As shown in Figure 13, the diffuser structure **1408** also optionally comprises the right mirror **1412** or provides an attachment point for such a mirror.

 While the above description makes reference to particular values, such as, but not limited to,
20 an E/N value of approximately 180 Td, it is understood to one of ordinary skill in the art that lower E/N values are within the scope of the present invention, for example, approximately 150 Td and below. The above description also makes reference to "plasma" which is used generally to describe a weakly ionized gas, for example, but not limited to, a gas with an electron density between approximately 10^{12} to approximately 10^{15} electrons/cm³.

Various embodiments of the present invention are useful for the following areas:

1. Energy and Nuclear Power - cut-up decommissioned reactor vessels, centrifuges, etc.; scabble radioactive layers from cement surfaces; and deep penetration welding, which may be performed robotically in contaminanted areas.

2. Marine and Heavy Equipment Industries - deep penetration welding, cutting and drilling; cladding, surface modification or texturing; removal of corrosion and sea debris, such as barnacles, from marine platforms and barges; and removal of coatings and special, rubber-like layers from vessels, such as, but not limited to, submarines, ships, and barges.

3. Civil Engineering - cleaning bridges, tunnels, outdoor storage tanks (inside and out); road texturing; and tunneling, mining, and rock fracturing.

4. Steel Industry - remove scale from steel rolls and steel roll butt-joint welding.

5. NASA/Space Industry - destruction/removal of space debris; meteor deflection from Earth and other objects; rocket propulsion from ground-based laser or from solar-powered, space-based laser (at any altitude above Earth's surface); deep space communications; and space power transmission.

6. Military Applications - Target designators and ground-based (fixed or mobile), airborne, or space-based weapons.

7. Automobile Applications - reducing emissions from automobile exhaust (as well as any other combustion engine).

The preceding examples can be repeated with similar success by substituting the generically or specifically described reactants and/or operating conditions of this invention for those used in the preceding examples.

Although the invention has been described in detail with particular reference to these preferred embodiments, other embodiments can achieve the same results. Variations and modifications of the present invention will be obvious to those skilled in the art and it is intended to cover in the appended claims all such modifications and equivalents. The entire disclosures of all references, applications, patents, and publications cited above are hereby incorporated by reference.

[illegible]